

How to upgrade APX-15 Firmware using the web interface

- Log into APX-15 on a browser that is connected to your APX-15 _
- From the Main Menu, select Firmware (see Figure 1) _

| Receiver Status |
|------------------------|
| Satellites |
| Web Services |
| Data Logging |
| Receiver Configuration |
| I/O Configuration |
| Network Configuration |
| Security |
| Firmware |
| Help |
| |

Figure 1: Main Menu, red outline depicting Location of Firmware

- Refer to Figure 2, and follow the next steps in order to load the Firmware -
- Using button "Chose File", browse to firmware image file that you want to load. _
- The firmware image file can be downloaded from the Support Section of the Applanix _ website.
- Press the button "Install New Firmware" in order to initiate installation _
- Please, make sure that browser is open and there is no power interruption until the _ upgrade process is completed.

| Install New Firmware | | |
|--------------------------------------|-------------|--|
| Firmware Warranty Date: | 2016-08-01 | |
| Pending Firmware Version: | 5.01 | |
| Active Core Engine Version: | 0.65 - 5.01 | |
| Active Firmware Release Date: | 2015-03-30 | |
| Active Firmware Warranty Date: | 2014-05-01 | |
| Active Firmware Checksum: | 7a6c7225 | |
| Choose File metallica_v5.00_096.time | 9 | |
| Install New Firmware | | |

Status: Idle

Figure 2: Firmware Installation